

# **HAPTIC FEEDBACK SENSATIONS BASED ON AUDIO OUTPUT FROM COMPUTER DEVICES**

BY INVENTOR

*Stephen D. Rank*

## **BACKGROUND OF THE INVENTION**

5  
10 The present invention relates generally to systems for allowing humans to interface with computer systems, and more particularly to methods for providing haptic feedback to the user interfacing with one or more computer applications involving sound output.

15 A user can interact with an environment displayed by a computer to perform functions and tasks on the computer, such as playing a game, experiencing a simulation or virtual reality environment, using a computer aided design system, operating a graphical user interface (GUI),  
20 navigate web pages, etc. Common human-computer interface devices used for such interaction include a mouse, joystick, trackball, gamepad, remote control, steering wheel, stylus, tablet, pressure-sensitive sphere, or the like, that is in communication with the computer system controlling the computer environment. The computer updates the environment in response to the user's manipulation of a physical manipulandum such as a joystick handle, button, or mouse, and provides visual and audio feedback to the user utilizing the display screen and audio speakers. The computer senses the user's manipulation of the user object through sensors provided on the interface device that send locative signals to the computer.

25 In some interface devices, kinesthetic force feedback and/or tactile feedback is also provided to the user, more generally known collectively herein as "haptic feedback." These types of interface devices can provide physical sensations which are felt by the user manipulating a user manipulandum of the interface device. One or more motors or other actuators are coupled to the manipulandum and are connected to the controlling computer system. The computer system controls forces on the manipulandum in conjunction and coordinated with computer events and interactions by sending control signals or commands to the actuators. The computer system can  
30 thus convey physical force sensations to the user in conjunction with other supplied feedback as the user is grasping or contacting the interface device or manipulatable object of the interface device.

The audio feedback provided to the user is an inherent part of many application programs, especially games. Some existing haptic feedback devices are designed to provide haptic

sensations based directly on the sound output from the computer. The sound output waveform is directly routed to the interface device so that tactile sensations, such as vibrations, are based directly on the sound output waveform or a filtered portion thereof, much like the way a speaker operates.

- 5           A disadvantage of existing haptic sensations based on direct sound waveforms is that the haptic sensations are simple effects based directly on the sound signals. No evaluation or processing of the sound signals is accomplished before sending the signals to the haptic device. This can cause undesirable or disconcerting haptic sensations to be output to the user since not all of the sound output is appropriate for directly translation into haptic sensations.

10

11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
2201  
2202  
2203  
2204  
2205  
2206  
2207  
220

## SUMMARY OF THE INVENTION

The present invention is directed toward triggering the output of haptic sensations based on sound output from a computer device. The output of haptic sensations is intelligently triggered by analyzing sound data for features, allowing an enhanced user experience.

More particularly, an interface device of the present invention provides a method for triggering haptic sensations from sound features detected in sound output from a computer, where the haptic sensations are able to be output to a user of a haptic feedback device in communication with the computer. A portion of sound data is stored that is output to a user as audio from an application program running on the computer. The sound data is stored in a memory buffer of the computer. The portion of sound data is analyzed using intelligent heuristics to extract at least one sound feature from the portion of sound data. The execution of at least one haptic effect is triggered based on the sound feature(s), where the haptic effect is commanded to the haptic feedback device approximately correlated to the output of the portion of sound to the user as audio. The haptic effect causes a haptic sensation to be output to the user.

The triggered haptic sensation is preferably assigned to the sound features found in the sound data. In some embodiments, analyzing the portion of sound data can include processing the sound data into multiple different frequency ranges and searching for sound features in each of the frequency ranges. A haptic effect can be triggered for each of the frequency ranges if the sound feature is present in that frequency range. Filters can be applied to the sound data, or a fast Fourier transform can be used. Each frequency range can be associated with or mapped to a different haptic sensation. For example, each of the frequency ranges can be associated with a periodic haptic sensation having a different frequency. Other types of haptic sensations can also be mapped and assigned to sound features so that they will trigger upon output of those sound features.

The present invention advantageously allows haptic feedback to be output by a computer system running an application program having sound output. The present invention intelligently assigns haptic sensations to features in the sound data to provide haptic feedback relevant to events in the application program which caused the sound output. This results in an overall improvement in user experience of the haptic feedback based on sound output.

These and other advantages of the present invention will become apparent to those skilled in the art upon a reading of the following specification of the invention and a study of the several figures of the drawing.

## **BRIEF DESCRIPTION OF THE DRAWINGS**

FIGURE 1 is a block diagram illustrating one embodiment of a haptic feedback system  
5 suitable for use with the present invention;

FIGURE 2 is a side cross-sectional view of a mouse embodiment of the haptic feedback  
device suitable for use with the present invention;

FIGURE 3 is a flow diagram illustrating a first embodiment of a method of the present  
invention for providing haptic effects to be output as haptic sensations based on provided sound  
data;

FIGURE 4 is a flow diagram illustrating one embodiment for the step of Fig. 3 in which  
the sound data stored in the buffer is processed and analyzed; and

FIGURE 5 is a flow diagram illustrating another embodiment for the step of Fig. 3 in  
which the sound data stored in the buffer is processed and analyzed.

## DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

FIGURE 1 is a block diagram illustrating a computer system 10 suitable for use with the present invention, including a haptic feedback interface device 12 in communication with a host computer 14.

Host computer 14 preferably includes a host microprocessor 20, a clock 22, a display screen 26, and an audio output device 24. The host computer also includes other well known components, such as random access memory (RAM), read-only memory (ROM), and input/output (I/O) electronics (not shown). The host computer 14 is a computing device that can take a wide variety of forms. For example, in the described embodiments computer 14 is a personal computer or workstation, such as a PC compatible computer or Macintosh personal computer, or a Sun or Silicon Graphics workstation. Such a computer 14 can operate under the Windows™, MacOS™, Unix, MS-DOS, or other operating system. Alternatively, host computer 14 can be one of a variety of home video game console systems commonly connected to a television set or other display, such as systems available from Nintendo, Sega, Sony, or Microsoft. In other embodiments, host computer 14 can be a “set top box”, a “network-” or “internet-computer”, a portable computer or game device, personal digital assistant (PDA), etc.

Host computer 14 preferably implements a host application program with which a user is interacting via device 12 and other peripherals, if appropriate. In the context of the present invention, the host application program is a digital audio editing program, as described in greater detail below. Other application programs that utilize input of device 12 and output haptic feedback commands to the device 12 can also be used. The host application program preferably utilizes a graphical user interface (GUI) to present options to a user and receive input from the user. This application program may include the haptic feedback functionality described below; or, the haptic feedback control can be implemented in another program running on the host computer, such as a driver or other application program. Herein, computer 14 may be referred as providing a “graphical environment,” which can be a graphical user interface, game, simulation, or other visual environment. The computer displays “graphical objects” or “computer objects,” which are not physical objects, but are logical software unit collections of data and/or procedures that may be displayed as images by computer 14 on display screen 26, as is well known to those skilled in the art. Suitable software drivers which interface software with haptic feedback devices are available from Immersion Corporation of San Jose, California.

Display device 26 can be included in host computer system 14 and can be a standard display screen (LCD, CRT, flat panel, etc.), 3-D goggles, projection device, or any other visual

output device. Display device 26 displays images as commanded by an operating system application, simulation, game, etc.

Audio output device 24, such as speakers, provides sound output to user. In the context of the present invention, other audio-related devices may also be coupled to the host computer, such as stereo receivers, amplifiers, etc. Other types of peripherals can also be coupled to host processor 20, such as storage devices (hard disk drive, CD ROM drive, floppy disk drive, etc.), printers, and other input and output devices.

The haptic feedback interface device 12, such as a mouse, knob, gamepad, trackball, joystick, remote control unit, PDA screen, etc., is coupled to host computer 14 by a bi-directional bus 30. The bi-directional bus sends signals in either direction between host computer 14 and the interface device. Bus 30 can be a serial interface bus, such as an RS232 serial interface, RS-422, Universal Serial Bus (USB), MIDI, or other protocols well known to those skilled in the art; or a parallel bus or wireless link. Some interfaces can also provide power to the actuators of the device 12.

Device 12 can include a local processor 40. Local processor 40 can optionally be included within the housing of device 12 to allow efficient communication with other components of the mouse. Processor 40 can be provided with software instructions to wait for commands or requests from computer host 14, decode the command or request, and handle/control input and output signals according to the command or request. In addition, processor 40 can operate independently of host computer 14 by reading sensor signals and calculating appropriate forces or commands from those sensor signals, time signals, and stored or relayed instructions selected in accordance with a host command. Suitable microprocessors for use as local processor 40 include the MC68HC711E9 by Motorola, the PIC16C74 by Microchip, and the 82930AX by Intel Corp., for example, as well as more sophisticated force feedback processors such as the Immersion Touchsense Processor. Processor 40 can include one microprocessor chip, multiple processors and/or co-processor chips, and/or digital signal processor (DSP) capability.

Microprocessor 40 can receive signals from sensor(s) 42 and provide signals to actuator 44 in accordance with instructions provided by host computer 14 over bus 30. For example, in a local control embodiment, host computer 14 provides high level supervisory commands to processor 40 over bus 30, and processor 40 decodes the commands and manages low level force control loops to sensors and the actuator in accordance with the high level commands and independently of the host computer 14. This operation is described in greater detail in US Patents 5,739,811 and 5,734,373, both incorporated herein by reference. In the host control loop, force commands from the host computer instruct the processor to output a force or force

sensation having specified characteristics. The local processor 40 reports locative and other sensor data to the host computer which the host computer uses to update executed programs. In the local control loop, actuator signals are provided from the processor 40 to actuator 44 and sensor signals are provided from the sensor 42 and other input devices 48 to the processor 40.

5 The processor 40 can process inputted sensor signals to determine appropriate output actuator signals by following stored instructions. Herein, the term "haptic sensation" or "tactile sensation" refers to either a single force or a sequence of forces output by the actuator which provide a sensation to the user. The term "haptic effect" generally refers to the commands, parameters, and/or data sent to the device that define a haptic effect and which results in a haptic

10 sensation when the effect is output as forces to the user by the device.

In yet other embodiments, other simpler hardware can be provided locally to device 12 to provide functionality as processor 40. For example, a hardware state machine or ASIC incorporating fixed logic can be used to provide signals to the actuator 44 and receive sensor signals from sensors 42, and to output tactile signals according to a predefined sequence, algorithm, or process.

15

In a different, host-controlled embodiment, host computer 14 can provide low-level force commands over bus 30, which are directly transmitted to the actuator 44 via processor 40. Host computer 14 thus directly controls and processes all signals to and from the device 12. In the simple host control embodiment, the signal from the host to the device can command the actuator to output a force at a predefined frequency and magnitude, or can include a magnitude and/or a direction, or be a simple command that indicates a desired force value to apply over time.

20

Local memory 52, such as RAM and/or ROM, is preferably coupled to processor 40 in device 12 to store instructions for processor 40 and store temporary and other data. For example, force profiles can be stored in memory 52, such as a sequence of stored force values that can be output by the processor, or a look-up table of force values to be output based on the current position of the user object. In addition, a local clock 54 can be coupled to the processor 40 to provide timing data, similar to the system clock of host computer 14; the timing data might be required, for example, to compute forces output by actuator 44 (e.g., forces dependent on calculated velocities or other time dependent factors). In embodiments using the USB communication interface, timing data for processor 40 can be alternatively retrieved from the USB signal.

25

30

Sensors 42 sense the position or motion of the device and/or one or more manipulandums or controls and provides signals to processor 40 (or host 14) including information representative of the position or motion. Sensors suitable for detecting manipulation include digital optical encoders, optical sensor systems, linear optical encoders, potentiometers, optical sensors,

35

velocity sensors, acceleration sensors, strain gauge, or other types of sensors can also be used, and either relative or absolute sensors can be provided. Optional sensor interface 46 can be used to convert sensor signals to signals that can be interpreted by the processor 40 and/or host 14.

5 Actuator(s) 44 outputs haptic sensations by transmitting forces to the housing or one or more manipulandums of the device 12 in response to signals received from processor 40 and/or host computer 14. Actuator 44 can be any of many types of actuators, including active actuators such as DC motors, voice coils, pneumatic or hydraulic actuators, torquers, piezoelectric actuators, moving magnet actuators, etc., or passive actuators such as brakes.

10 Actuator interface 50 can be optionally connected between actuator 44 and processor 40 to convert signals from processor 40 into signals appropriate to drive actuator 44. Interface 50 can include power amplifiers, switches, digital to analog controllers (DACs), analog to digital controllers (ADCs), and other components, as is well known to those skilled in the art. Other input devices 48 are included in device 12 and send input signals to processor 40 or to host 14 when manipulated by the user. Such input devices can include buttons, scroll wheels, d-pads, 15 dials, switches, or other controls or mechanisms.

Power supply 56 can optionally be included in device 12 coupled to actuator interface 50 and/or actuator 44 to provide electrical power to the actuator, or be provided as a separate component. Alternatively, power can be drawn from a power supply separate from device 12, or be received across the bus 30. Also, received power can be stored and regulated by device 12 and thus used when needed to drive actuator 44 or used in a supplementary fashion. Some 20 embodiments can use a power storage device in the device to ensure that peak forces can be applied (as described in U.S. Patent No. 5,929,607, incorporated herein by reference). Alternatively, this technology can be employed in a wireless device, in which case battery power is used to drive the tactile actuators. A safety switch 58 can optionally be included to allow a 25 user to deactivate actuator 44 for safety reasons.

Many types of interface or control devices may be used with the present invention described herein. For example, such interface devices can include a haptic feedback trackball, joystick handle, steering wheel, knob, handheld remote control device, gamepad controller for video games or computer games, stylus, grip, wheel, button, cellular phone, PDA, touchpad, or 30 other manipulatable object, surface, or housing.

FIGURE 2 is a side cross-sectional view of a mouse embodiment 100 of device 12 for use with the present invention.



Mouse device 100 includes a housing 101, a sensing system 102, and an actuator 104. Housing 101 is shaped to fit the user's hand like a standard mouse while the user moves the mouse in the planar degrees of freedom and manipulates the buttons 106. Other housing shapes can be provided in many different embodiments.

5        Sensor 102 detects the position of the mouse in its planar degrees of freedom, e.g. along the X and Y axes. In the described embodiment, sensor 102 includes a standard mouse ball 110 for providing directional input to the computer system. Alternatively, an optical sensor or other type of sensor can be used.

10        Mouse device 100 includes one or more actuators 104 for imparting haptic feedback such as tactile sensations to the user of the mouse. Actuator 104 is coupled to the housing 101 to provide haptic feedback to the user. In one embodiment, the actuator is coupled to an inertial mass that is moved by the actuator. Inertial forces caused by the motion of the inertial mass are applied to the housing of the mouse with respect to the inertial mass, thereby conveying haptic feedback such as tactile sensations to the user who is contacting the housing. Some  
15        embodiments allow the actuator to move itself as the inertial mass. Such embodiments are described in greater detail in U.S. Patent No. 6,211,861 and U.S. Application No. 09/585,741, both incorporated herein by reference. Other types of interface devices, such as gamepads, handheld remote controls, cellular phones, PDA's, etc., can include such an actuator for inertial tactile sensations.

20        Other types of interface devices and actuators can also be used with the present invention. For example, gamepads, mice, or other devices can include an eccentric rotating mass coupled to a rotating shaft of an actuator to provide inertial tactile sensations on the housing or manipulandum of the device. Other types of haptic devices can provide kinesthetic force feedback, such as joysticks, knobs, scroll wheels, gamepads, steering wheels, trackballs, mice,  
25        etc., in which forces are output in the sensed degree(s) of freedom of a manipulandum. For example, embodiments of a kinesthetic mouse haptic device are disclosed in U.S. Patent Nos. 6,100,874 and 6,166,723, both incorporated herein by reference in their entireties.

#### Sound Output with Haptic Feedback

30        The present invention improves the user experience in the output of haptic sensations coordinated with the sound output of one or more application programs (or other programs) running on the host computer.

The preferred embodiment of the present invention provides haptic effects for output to a haptic feedback device based on sound signals or data output by a host computer and which are output as haptic sensations to the user. In some alternate embodiments, the haptic effects can be similarly provided based on features in sound signals or data input to a computer system, e.g. from a microphone or audio device. Temporal features and characteristics of sound are identified and mapped to or associated with preprogrammed haptic effects. The haptic sensations based on these haptic effects can be rendered immediately on haptic feedback device 12, or can be stored in memory to form a "haptic profile" of a given sound. The method of the present invention is not to simply route sound signals directly to a haptic device for output as haptic sensations, as is done in the prior art, but to associate a variety of high-level sound features with a variety of high-level haptic sensations, using the sound features to trigger the output of the appropriate haptic sensations.

An important advantage of the present invention is that compelling haptic sensations are provided for any program that outputs sounds for a variety of events in that application program, e.g. games, without a software application developer having to expend effort in programming the haptic effects in the program. Thus, any game program off the shelf can be easily made to work with haptic feedback devices regardless of whether the game includes code to control haptic devices or whether it was only developed for non-haptic-feedback devices, allowing the user a more compelling interactive and immersive experience with a wide variety of programs. Furthermore, the present invention can approximately distinguish between types of sound effects and associate different haptic sensations with different events, allowing a more rich experience for the user.

In one embodiment, a low-level driver program running on the host computer performs the methods of the present invention. In other embodiments, other levels of software running on the host (or on a microprocessor of the haptic feedback device) can perform some or all of the features or steps of the present invention (application program, API, etc.). Program instructions for implementing the present invention can be stored as hardware (e.g. logic components) or software stored on a computer readable medium, such as electrical memory, magnetic disk, optical disk, magnetic tape, etc.

FIGURE 3 is a flow diagram illustrating a first embodiment 200 of a method of the present invention for providing haptic effects to be output as haptic sensations based on given sound data or sound signal. The method starts at 202, and in optional step 204, haptic effects are commanded to the device and not yet output to the user. For example, the haptic device 12 can include local memory that allows the device to store data for a number of different haptic effects. The haptic effects resident in the device memory can be played when a host command is received or based on other conditions (a predetermined time period has passed, etc.). The data sent to the device can include parameters for the haptic effects; e.g., for a periodic vibration effects, the parameters can

include a frequency, duration, and magnitude. The effects can be loaded to the device in step 204 and in some embodiments can be commanded to play, e.g. at a magnitude of zero, in preparation to be commanded to higher magnitudes at a later step. Step 204 is most appropriate for those embodiments in which the same set of haptic sensations are always output to the user. In other  
5       embodiments, haptic effects can be commanded at the time they are to be output to the user.

In next step 206, sound data is received from an application program or other software layer or program running on the host computer, or alternately, direction from an external audio device. The sound data is preferably digital data that can be in any standardized format, such as MIDI, digital  
10       sound samples in a wav file, an mp3 file, etc. The sound data is received in step 206 when it is also to be routed to an audio output device such as speakers and output to the user as sound. Typically, the sound data is generated by the application program from a sound event occurring in the application, such as a sound effect in a game resulting from game actions or events, music in a game or other application program playing after a game starts or other event occurs, a beep in a graphical  
15       user interface interaction, the playing of music from a CD or DVD, or other sound event. In the described embodiment, the sound data received at this step to be analyzed is currently being output by speakers to the user. Thus, by the time the sound data is processed and haptic sensations output as described below, the sound data has already been output to the user. However, since a small amount of sound data is stored, only a delay of milliseconds occurs between sound and haptic output, which the user cannot discern. In other embodiments in which the sound data output is known in  
20       advance, haptic sensations can be output simultaneously, or close to simultaneously, with the sound data that triggered them.

In step 208, a predetermined amount of the received sound data is stored in a temporary buffer in the memory of the host computer 14. In one embodiment, this is an amount of data reasonably small enough to allow quick processing and associating with haptic sensations, while  
25       large enough to permit meaningful processing and analysis. In one embodiment, a portion of sound data equivalent to about 10 ms of play is stored, although different amounts can be stored in other embodiments. For example, the sound can be digitally recorded in a 10 ms segment using DirectSound or other sound capture API on the host computer.

In step 210, the stored sound data is processed and analyzed to identify particular sound  
30       characteristics or features which have been designated as relevant in the determination of which haptic sensations are to be output, i.e. these sound features are to act as cues to trigger the output of haptic sensations. In broad terms, the present invention uses intelligent heuristics to extract sound features that are likely to have meaning in an application program and to associate such sound features with predetermined, preprogrammed haptic sensations that correspond appropriately with  
35       the extracted sound features and the likely events these features represent. For example, likely

events in many current video game applications may be explosions from bombs, grenades, missiles, etc., the firing of a weapon such as a gun or rocket, the crash of a vehicle, the patter of footsteps, the sound of an object splashing into water, an alert sound for alerting the player to some game event, etc. These events may have particular sound features which can be recognized from the received sound data after appropriate analysis.

A variety of different ways can be employed to process the data; some embodiments are described below with respect to Figs. 4 and 5. These particular embodiments perform processing on the sound data to divide the waveform represented by the sound data into a number of different frequency ranges according to the present invention. Each frequency range of sound can then be analyzed separately for particular sound features. This frequency range division has the advantage that sounds often occur in different frequency ranges based on the event that triggered the sound; for example, an explosion in a game may have a low frequency sound while a gun shot may have a higher frequency sound. Types of events might therefore be approximately distinguished based on the frequency range in which the sound is located, allowing different haptic effects to be commanded and output as described below.

Once the sound data has been processed and analyzed, in next step 212, haptic commands are output to the haptic device to cause haptic sensations to be output to the user manipulating the device. The haptic commands are triggered based on the sound features, if any, found in the sound data in step 210. Intelligent heuristics can be used to assign different haptic sensations to different types of sounds based, for example, on the frequencies of the sounds or other characteristics of the sounds. The haptic commands can cause device-resident haptic effects to start playing or play at a commanded magnitude. In one embodiment, the haptic effects that are already resident in memory on the device from step 204 are modified with new parameters or data as appropriate to implement the desired haptic sensations. Alternatively, new haptic effects can be created and commanded to be output immediately by the device as haptic sensations. As explained above, the haptic sensations resulting from the commands may be output slightly after the associated sound features have been output as audio, but preferably soon enough so that the user cannot tell that there was a delay.

In one embodiment, the commanded haptic sensations can be set to a magnitude proportional to the sound data magnitude in the associated frequency range. For example, embodiments discussed with reference to Figs. 4 and 5, the sound data is filtered or organized into 5 different frequency ranges. Each of these frequency ranges can have a different haptic sensation associated with it. For example, using an available inertial tactile feedback mouse, a periodic haptic effect of different frequency is associated with each of the frequency ranges. Thus, for example, a periodic haptic effect having a haptic frequency of 62 Hz (e.g., at or near a first resonance frequency of the haptic device to cause high magnitude sensations) is associated with the first sound frequency range (e.g., 0

Hz to 150 Hz). The other periodic haptic effects can have haptic frequencies of 75 Hz, 90 Hz, 115 Hz, and 250 Hz, each corresponding to another sound frequency range in ascending order (other periodic frequencies can be used in other embodiments). The magnitudes of each of these periodic haptic effects can be set to a value proportional to the magnitude of the sound data in the associated frequency range. A running average of magnitude of ambient sound levels can be used as a minimum threshold for haptic effect generation, e.g. if the sound signal for a particular frequency range has a higher magnitude than the threshold, then a haptic effect associated with that frequency range can be commanded to be output or can be commanded to have a magnitude above a zero level.

The method presented above thus varies the magnitudes of five different haptic effects based on the corresponding varying magnitudes in different frequency ranges of the sound signal represented by the sound data. With some sounds that have components in all the frequency ranges, this may cause five different haptic effects to be output at once. However, since many sound features that are spread across several frequency ranges last for a short amount of time, the user perceives only a short vibration or series of pulses rather than a mush of different frequencies. Other more sustained sound effects may be concentrated in only one or two frequency ranges which will cause only one or two haptic effects to be output simultaneously (the haptic effects for the other frequency ranges will be set to zero magnitude). The user will thus feel a haptic sensations that roughly corresponds to the sound effect's frequency. This is also discussed with respect to Fig. 4.

Thus, the amplitude of a haptic sensation that is associated with a particular frequency range or band can correspond directly with the magnitude level of a sound signal in that frequency band, as explained above. In addition to this continuous haptic output, sudden spikes of amplitude in the sound signal can be mapped to additional jolts, pulses, or other short, strong haptic sensations which can be overlaid on the continuous vibration sensations.

In other embodiments, more sophisticated haptic sensations can be output based on the sound data processing and analysis of step 210 and based on intelligent heuristics. In many applications such as games, the type of sound may be able to be determined based which frequency ranges it is primarily located. This allows a more sophisticated mapping scheme, where completely different haptic sensations can be mapped to different sound frequency ranges. This is also discussed with respect to Fig. 5.

For example, it is often the case that weapon fire in a video game application is associated with a sudden burst of high frequency sound. Using this fact as an intelligent heuristic, in step 210 the sound output data from the game can be analyzed and a feature that indicates that a high frequency sound has been output identified. For example, a particular frequency range can be checked for a sudden burst or spike in amplitude of sound. In step 212, a haptic sensation associated with weapon fire can be intelligently commanded to be output based on the sound burst found in the

sound. In some embodiments, the haptic sensation can be modified on the fly while the sound and the haptic sensations are playing, where the magnitude and duration of the haptic sensation is continually adjusted based on the magnitude of the sound burst above a predetermined threshold, the duration of the burst, and/or the specific frequency content of the burst.

5 In some embodiments, a completely different haptic profile can be selected for a sound feature based on the specifics of the sound feature, where a pre-programmed mapping between sound characteristics and haptic effects is consulted (e.g., a look-up table or data table can be stored in memory). For example, a sound burst in a very different frequency range might trigger a completely different haptic sensation. A low frequency sound burst in a video game might be, for example, the  
10 sound of a footstep of a character. An appropriate haptic sensation can be mapped to that sound feature, such as a low-frequency vibration or undulating force.

Some games or other programs may output similar sound effects for similar events to allow approximate mapping as discussed above. Other games and programs, however, may have different events associated with similar-sounding sounds. Therefore, in one embodiment, a particular look-up  
15 table or other mapping data can be associated with each individual game (or other application program). Using the table, the method of the present invention can identify on the table which game is playing and then find the appropriate mapping between sound characteristics of that game and haptic sensations that have been assigned by the table's author. This allows for tuning of the heuristics tailored for specific games, enabling more accurate mappings. This can be advantageous  
20 to developers, who will not have to put haptic effects or mappings in their games themselves, but can rely on the manufacturers of the haptic devices to put out driver updates including haptic mappings for games currently available based on the sound output.

In alternate embodiments, the haptic effects that are associated with the found sound features are not immediately output as haptic sensations to the user, but are instead stored in memory to form  
25 a "haptic profile" of a given sound. This can be used to assist in the design of haptic effects. For example, a sound file can be loaded and the user can select a control in a graphical user interface to cause the method of the present invention to generate a compound haptic effect that corresponds to the sound. The generated haptic effect (or haptic magnitudes, force values, etc.) can be then used in a program by commanding the generated compound haptic effect. Alternatively, the haptic profile  
30 (generated effect) can become a new haptic effect primitive to allow developers to create new effects based on this primitive, e.g. periodic effects, textures, temporal profiles, etc. can be created.

For example, a game may have hundreds of sound effects. The method of the present invention can be instructed to load the game's sound files and create haptic effects from the sound data in a standardized format (such as .ifr files, used in protocols created by Immersion Corp. of San  
35 Jose, California) in a few seconds. Thus, a developer need not create each haptic effect manually,

saving great amount of development time. A designer could also examine the generated haptic effects and edit them, if desired. This is advantageous to developers who wish to add code to their games to command haptic effects to haptic devices in the traditional way, but who do not wish to spend large amounts of time designing the appropriate haptic effects.

5 After the output of the haptic sensation, the method returns to step 206 to check if further sound data is received. If so, a next portion of sound data is processed as discussed above. If no further sound data is received, the process is complete at 242 (to be started again the next time sound data is output).

10 FIGURE 4 is a flow diagram illustrating one embodiment for step 210 of Fig. 3, in which the sound data stored in the buffer is processed and analyzed. The method starts at 270, and in step 272, the stored sound data is set through multiple filters to isolate different frequency ranges. For example, to divide the sound data into five frequency ranges as described in the example above, a low-pass filter, a high-pass filter, and three bandpass filters can be employed. As one example, the low-pass filter can filter out all data in the frequencies outside 0-170 Hz, the first bandpass filter can  
15 filter out all frequencies except 170-430 Hz, the second bandpass filter can filter out all frequencies except 430 Hz-2 kHz, the third bandpass filter can filter out all frequencies except 2 - 10 kHz, and the high-pass filter can filter out all frequencies lower than 10 kHz.

20 In step 274, a running average of the sound magnitude from each of the filter outputs is maintained. This allows ambient sounds output from the computer to be averaged out so that only sounds louder than the ambient level will trigger haptic sensations. In next step 276, the magnitudes of the filter outputs are scaled to a range that is required for the haptic device 12 that the user is using. Thus, the actual filter outputs are not used to generate haptic sensations as in the prior art, but new haptic commands and effects are created based on the filter outputs.

25 In some embodiments, the square of each filter's output magnitude can be scaled. This may be more effective in some embodiments to pick out only the larger peaks or spikes in each frequency range of sound data and reduce a sustained rumble/vibration of the device that may occur from too many peaks being detected.

30 In next step 278, periodic haptic effects are assigned to each of the filter's outputs. The periodic effects can each be assigned a magnitude equal to the scaled magnitude found for each filter. If a filter has no output, i.e. no sound of that frequency range is present in the sound data, or if a filter's output is not above a predetermined threshold amplitude, then the haptic effect assigned to that frequency range would be assigned a magnitude of zero. The periodic sensations can each have one of five haptic frequencies found to be effective in conveying the corresponding sound frequency. Such periodic haptic sensations, such as vibrations, are quite appropriate for tactile devices such as

gamepads or mice providing inertial tactile sensations. The vibrations can also be output by kinesthetic feedback devices. Other types haptic sensations can also be output by kinesthetic device embodiments, having magnitudes based on the scaled magnitudes determined above. The type of haptic sensations assigned can be different in different embodiments, such as pops, jolts, springs, damping, etc., can also be output having magnitudes based on the scaled magnitudes; for example, a pre-programmed mapping can be consulted to assign a mapped haptic effect.

The method is then complete at 280. The assigned periodic haptic sensations can be used in the next step 212 of Fig. 3, where haptic sensations are output to the user by commanding the haptic effects to the haptic feedback device.

FIGURE 5 is a flow diagram illustrating a different embodiment 210' of step 210 of Fig. 3, in which the sound data stored in the buffer is processed and analyzed. The method starts at 290, and in step 292, a Fast Fourier Transform (FFT) is performed on the sound data to filter the data into different frequency components of the data's frequency spectrum. The frequency components each span a frequency range based on the number of components output by the FFT and the entire frequency range covered. For example, if the FFT has 512 outputs, and the entire frequency range of the sound data is about 22 kHz, the each FFT output frequency component has a frequency range of  $22 \text{ kHz} / 512 = \text{about } 43 \text{ Hz}$ . These frequency components can then be grouped to sum to desired frequency ranges. For example, to achieve the five frequency ranges similar to the embodiment of Fig. 4, four components can be combined to cover the first frequency range of 0 - 170 Hz, 6 components cover the range 170-430 Hz, 37 components cover the range 430 Hz - 2 kHz, 185 components cover the range 2 kHz - 10 kHz, and 256 components cover the range 10 - 22 kHz. Other frequency ranges and components can be used in other embodiments.

In next step 294, the method checks whether any of the frequency ranges grouped in step 292 have predetermined characteristics. These characteristics are features in the sound data that are significant enough to trigger the output of haptic sensations. In one embodiment, an average amplitude is maintained for each frequency range, and a spike in the amplitude is looked for. If a spike in amplitude of 3-4 times the average amplitude is found, then that is deemed significant and a haptic effect should be assigned to or triggered by that feature.

If predetermined characteristics are found, then the process continues to step 296 to assign haptic effects to those frequency ranges having the predetermined characteristics, and the process is complete at 298 and the method returns to step 212 of Fig. 3. If in step 294 no frequency ranges are found to have the desired characteristics, then the process is complete at 298 and the method returns to step 212 of Fig. 3.



The haptic effects that are assigned to the frequency ranges having the desired characteristics can be any of several different types and/or have different parameters, and need not have a magnitude proportional to the amplitude of the corresponding sound data. For example, a jolt, pulse, or detent can be mapped to any extracted sound features (such as rise in amplitude). The magnitude of the jolt or detent can be based on the frequency range in which the amplitude spike was found, e.g. lower frequency ranges can be assigned higher magnitude haptic sensations (or vice-versa). Periodic sensations, directional sensations (for haptic devices able to output forces in particular directions in degrees of freedom of the device), spring sensations, damping sensations, etc. can be mapped to the different frequency ranges. In one embodiment, a haptic sensation can be increased in magnitude corresponding to the increased sound data amplitude, then the haptic amplitude can be ramped down automatically back to a zero level. Again, a pre-programmed mapping between sound features and haptic sensations can be consulted.

The FFT outputs of the embodiment of Fig. 5 tend to be more efficient and provide more information than the filter outputs of the embodiment of Fig. 4. For example, FFT's can provide more detailed frequency information about where a spike in amplitude occurs, the phase offset of waves or features in the sound signal, etc. It should also be noted that the assigning or triggering of different types of haptic sensations described above for Fig. 5 can also be performed in the embodiment of Fig. 4, and the magnitudes of haptic sensations proportional to sound amplitudes of Fig. 4 can be performed in the embodiment of Fig. 5.

In some applications, the ambient background sounds, such as background music in game applications, can be ignored so that only sound effects in the game trigger haptic sensations to be output. Often, the sound effect magnitudes are much higher than the background music amplitudes, allowing the sound effects to be found as spikes above an average amplitude. In other circumstances, background music can ignored and sound effects processed by the type of audio data. For example, if the background music is in a MIDI format and the sound effects are .wav files, then MIDI data can be ignored and wav data processed by the present invention to provide haptic sensations.

Some embodiments can also allow the user to enter preferences which can adjust how the sound data is analyzed, how the haptic effects are assigned, and how the haptic sensations are output. For example, haptic effect strength, the minimum threshold level of amplitude to recognize a sound feature (e.g., so that background music can be better ignored in a game), etc.

The present invention can also be used in other types of application programs besides games. For example, a user's experience of streaming audio can be enhanced by adding haptic sensations to the audio output, so that if the user is contacting the haptic device while listening to the audio output, features in the audio such as music beats, sustained notes, features of speech etc. can be haptically

experienced by the user. Likewise, the present invention can be used with a sound track that is output with streaming video, e.g. over a network such as the Internet.

While this invention has been described in terms of several preferred embodiments, it is contemplated that alterations, permutations and equivalents thereof will become apparent to those skilled in the art upon a reading of the specification and study of the drawings. For example, many different embodiments of haptic feedback devices can be used to output the haptic sensations described herein, including joysticks, steering wheels, gamepads, and remote controls. Furthermore, certain terminology has been used for the purposes of descriptive clarity, and not to limit the present invention.